

Controlling Multiple Vi305 DVRs from a Vi-K1

Menu configuration

To enable multiple unit control you need to set a unit address for the Vi305's, each unit needs a different address:

1 (master), 2, 3 etc

To set the address you need too select Menu then using the arrow keys select Configuration menu, now select Multi unit configuration. Select a unique address and select the number of linked units.

Control

Press and hold "LIVE" key then press "1" key. The Vi-K1 will now be addressing unit 1.

Press and hold "LIVE" key then press "2" key. The Vi-K1 will now be addressing unit 2.

Press and hold "LIVE" key then press "3" key. The Vi-K1 will now be addressing unit 3.

Up to 10 DVRs can be controlled from a Vi-K1

Once you have selected the VI305 you want control you use the keypad as normal.

Cabling

Connect the units together following the configuration drawing.

The input to the VI305 is via the main keyboard input pins 1 & 2

The output from the VI-K1 is via the out port pins 1 & 2

You will also need a star expander to control multiple units the VI-E2 is suitable for this application.

